SENNHEISER

Sonite R

Product information



Product description

Premium performance



		Sonite R
Multi-function button		•
Telecoil		
Bluetooth®		•
Hydrophobic coating		•
IP rating		IP68[1]
Dimensions	L x W x D	27.7 x 12 x 8.1 mm (1.09 x 0.47 x 0.32”)
	Weight	2.2 g (0.08 oz)
Charging times[2]	0% to 100%	3 h
	0% to 80%	1.5 h
	30 min. fitting	15 min.
S Receiver		
Max. Power Output (dB SPL)	2 cc coupler	111
Max. gain (dB)	2 cc coupler	47
Frequency range (Hz)		<100 - >8000
M Receiver		
Maximum Power Output (dB SPL)	2 cc coupler	114
Max. gain (dB)	2 cc coupler	51
Frequency range (Hz)		<100 - >8000
P Receiver		
Maximum Power Output (dB SPL)	2 cc coupler	122
Max. gain (dB)	2 cc coupler	59
Frequency range (Hz)		<100 - 6300 (CeruShield) <100 - 5900 (CeruStop)
UP Receiver		
Max. Power Output (dB SPL)	2 cc coupler	132
Max. gain (dB)	2 cc coupler	71
Frequency range (Hz)		<100 - 6100

Automatic	
Echo	•
Car	•
Loud Noise	•
Music	•
Comfort	•
Noise	•
Quiet	•
Streamed speech	•
Streamed music	•
Additional programs	
Max. additional programs	4
Echo	•
Loud Noise	•
Speech Direct	•
Noise	•
Quiet	•
Comfort	•
Music	•
Acoustic phone	•
Custom program	•
Streaming programs	
PartnerMic + mic	•
Phone call + mic	•
Remote Control	•

Features	
Speech Manager	•
Speech Boost	•
Narrow Speech Focus 2.0	•
Dynamic Noise Manager	•
Motion Sense	•
Directional Microphone	•
Echo Manager	•
Touch Control - Siri/Google Assistant - Pause/resume streaming - Accept/end phone call	•
Impulse Manager	•
DuoTel	•
Real Ear Effect	•
Health	•
Wind Manager	•
User Preference Tuning	•
Adaptation Control	•
HiFrequency Protect+	•
Feedback Manager	•
Noise Manager	•
Binaural Sync	•
AOV	•
Finetuning channel	20

1 IP68 indicates that the hearing aid is water and dust resistant. It survived continuous immersion in 1 meter of fresh water for 60 minutes and 8 hours in a dust chamber as per the IEC60529 standard.
2 Actual charging time depends on the remaining battery life, but it will not exceed 3 hours.

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Sonova AG is under license.

Housing colors



H0
Beige



P3
Sandalwood



P6
Silver Gray



P8
Velvet Black


Fitting

	Sonite R
Target	10.0 or higher
Noahlink Wireless, Noahlink Wireless 2	•


Acoustic coupling

		S Receiver	M Receiver	P Receiver	UP Receiver
Length					
Available in four different lengths (0, 1, 2, 3), left and right		•	•	•	•
Dome					
Cap dome		•	•	•	
Open dome	Available in three sizes (S, M, L)	•	•	•	
Vented dome	Available in three sizes (S, M, L)	•	•	•	
Power dome	Available in three sizes (S, M, L)	•	•	•	
SlimTip*					
Acrylic		•	•	•	
Silicone		•	•	•	
cShell					
Acrylic		•	•	•	•
Titanium		•	•	•	•
Fitting ranges					


*Available with extra canal length option




Mild to moderately-severe hearing loss.



Mild to severe hearing loss.



Mild to severe hearing loss.



Moderate to profound hearing loss.

Sonite R charging options



Sonite Charger R
The Sonite Charger is a compact charger with magnets in the charging slots that make it easy to insert and remove Sonite R. It uses a standard USB-C charging port that lights up when power is applied.

Sonite R Bluetooth® versions

Direct calls / audio streaming	Bluetooth 4.2 wireless technology and most older Bluetooth phones

Compatible wireless communication portfolio

The following accessories are compatible with Sonite R and designed to further improve your hearing in certain situations.

	Sonite R
Wireless accessory	
Easy Line TV Connector	•
Easy Line PartnerMic	•
Easy Line RemoteControl	•
Apps	
Easy Line Remote	•

For more information, visit **hearingaids.sennheiser-hearing.com**

Sennheiser is a registered trademark of Sennheiser electronic SE & Co. KG and is used under license by Sonova.

Sonova AG · Laubisrütistrasse 28
CH-8712 Stäfa · Switzerland

0459

7 613389 745580

027-0708-02/V2.00/20025-02/hc © 2024–2025 Sonova AG. All rights reserved.